Shihlin Sürücülerde Yön Değişim Komutlarında Dönüş Bekleme Süresi

Shihlin SC3 serisi inverterlerde Motor, ileri yönde dönüyor iken geri sinyali yada geri yönde dönüyorken ileri yön sinyali geldiğinde sürücü yavaşlama rampasını tamamlar ve gecikme olmaksızın devir önü değişir. Her yön değişimi komutunda bekleme süresi girilmesi isteniyor ise **10-16** parametresine saniye cinsinden bu değer girilebilir.

Örneğin: Sürücü 50.00 Hz de ileri yönde hareket ediyor iken Sürücüye geri çalışma sinyali gelir ise Sürücü yavaşlama rampası ile duruşa geçecek yavaşlama rampasını tamamladıktan sonra **10-16** Parametresine girilen saniye kadar bekleyecek daha sonra Hızlanma rampası ile geri yönde start alacaktır.

Parameter	Name	Default	Setting Range	Content
10-16 P.119	Forward and reverse rotation dead time	0.0s	0	Off.
			0.1~3000.0s	Waiting and holding time during forward -reverse switch, after inverter output frequency drops to zero

Setting Dead time of forward -reverse rotation

- Dead time of forward -reverse rotation refers to the waiting and holding time of inverter. During this period of time, inverter will transit from the current direction to the reverse direction upon receiving a reverse run command, and its output frequency will drop to zero.

  The diagram is as follows:

